

INTERCOM ENTRY SYSTEM - PANASONIC CAMERA



MODEL 800 ENTRY SYSTEM for PANASONIC NETWORK CAMERA - POLE MOUNT

- Designed for WV-ST165 or other similar cameras
 - Camera is not included - it is to be supplied by dealer
 - **Integrated 12 vDC power supply** (requires only one power supply-included)
 - “Draw bridge” hinges hold unit in **horizontal position for easy service**
 - **Tamper switch** output can be connected to alarm system
 - **Auxiliary bell contact** provided for automation system or camera / DVR
 - **Illuminated Essex piezo bell button**
 - **Illuminated keypad**
- Specify **keypad** type desired: Serial ASCII output **800-A**
Output for C2N-IIF **800-CR**
Stand-alone 12 button **800-S12**
26 Bit Wiegand output **800-W**

- Box dimensions 9.1” x 6.8” x 6.25” (h w d)

MODEL 800-X-CR - Crestron version -Includes **C2N-IIF**

MODEL 800-X-VIK* - High performance version using **Viking** components. System uses “half-duplex” communication, allowing for high speaker and microphone volume. . *OPTION: Upgrade to EWP (Enhanced Weather Protection) intercom*

For **Panasonic**, use 800-X-VIK with **PAN-1** adapter

MODEL 800-X-VIO - VoIP Intercom Module for standard SIP or **Crestron RavaSIP**. VIO features on-board IP switch for Panasonic IP camera (one Cat 5 for audio and video).

MODEL 800 OPTIONS

- *Brushed stainless steel -*
- *Oil Rubbed Bronze Finish - brass faceplate in ORB finish*

NOTE: The “X” in the part numbers above is to specify the keypad type. See above for keypad options.